


AD-A083 122

RCA CORP LANCASTER PA SSD-ELECTRO-OPTICS AND DEVICES F/6 9/1  
MANUFACTURING METHODS AND TECHNOLOGY MEASURE FOR FABRICATION OF--ETC(U)  
OCT 79 B B ADAMS, M F DEVITO, W L KROWN DAAK70-78-C-0120  
NL

UNCLASSIFIED

1 OF 1  
AD  
A083122



END

DATE

FILED

DTIC

Manufacturing Methods and Technology Measure  
for Fabrication of Silicon Transcendent Rectifier  
Interim Technical Report

Period Covered:

17 December, 1978 through 22 October, 1979

Contract No. DAAK70-78-C-0120

Prepared by:

B. B. Adams  
M. F. DeVito  
W. L. Krown  
R. E. Reed

DISTRIBUTION STATEMENT A

Approved for public release;  
Distribution Unlimited

## SUMMARY

This report describes in detail the more important steps in the fabrication and testing of the confirmatory samples of the MM&T Silicon Transcendent Rectifier program. Factors used in the selection of the prototype design are presented. The data from all ten confirmatory samples including description of test circuits and test results are contained herein as well as some decision making data taken on additional devices.

The ten confirmatory sample devices successfully passed all of the inspections required by the contract. All devices were then shipped to MERADCOM on September 18, 1979. Government acceptance of the shipment is awaited.

Accession For	
NTIS GR&I	<input checked="checked" type="checkbox"/>
DDC TAB	<input type="checkbox"/>
Unannounced	<input type="checkbox"/>
Justification	
By	
Signature	
Classification Codes	
Serial/	
Total	
A	

Unclassified

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

REPORT DOCUMENTATION PAGE		READ INSTRUCTIONS BEFORE COMPLETING FORM
1. REPORT NUMBER	2. GOVT ACCESSION NO.	3. RECIPIENT'S CATALOG NUMBER
4. TITLE (and Subtitle) Manufacturing Methods and Technology Measure for Fabrication of Silicon Transcendent Rectifier		5. TYPE OF REPORT & PERIOD COVERED Interim Report 17 Dec 1978-22 Oct 1979
6. AUTHOR(s) B. B. Adams W. L. Krown M. F. DeVito R. E. Reed		7. CONTRACT OR GRANT NUMBER(s) DAAC 78-78-C-0120
8. PERFORMING ORGANIZATION NAME AND ADDRESS RCA Corporation SSD-Electro Optics & Devices New Holland Avenue Lancaster, PA 17604		9. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS Confirmatory Sample Phase
10. CONTROLLING OFFICE NAME AND ADDRESS U.S. Army Mobility Equipment R&D Command Procurement and Production Directorate Fort Belvoir, VA 22060		11. REPORT DATE Oct 1979
12. MONITORING AGENCY NAME & ADDRESS (if different from Controlling Office) 1A) 64		13. NUMBER OF PAGES 66
		14. SECURITY CLASS. (of this report) Unclassified
		15a. DECLASSIFICATION DOWNGRADING SCHEDULE
16. DISTRIBUTION STATEMENT (of this Report) Approved for public release; distribution unlimited, except that the information presented is not to be construed as a license to manufacture or sell the device described without permission.		
17. DISTRIBUTION STATEMENT (of the abstract entered in Block 20, if different from Report)		
18. SUPPLEMENTARY NOTES		
19. KEY WORDS (Continue on reverse side if necessary and identify by block number) Environmental testing      Statistical analysis      Heat-Pipe Ion implanted      Transcendent Rectifier      Power Diode Webless wick      "Go", "No-Go" gauge      Isothermal Convolute and nonconvolute      Thermal resistance		
20. ABSTRACT (Continue on reverse side if necessary and identify by block number) RCA has successfully completed the fabrication and testing of the ten confirmatory samples. This report thoroughly describes the test results as well as the basis for selecting the prototype design. It also includes a picture or block diagram of each test circuit utilized. All devices passed all inspections with a yield of 100%.		

DD FORM 1473

1 JAN 73


EDITION OF 1 NOV 65 IS OBSOLETE

Unclassified 410148

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

Unclassified

SECURITY CLASSIFICATION OF THIS PAGE(When Data Entered)



Unclassified

SECURITY CLASSIFICATION OF THIS PAGE(When Data Entered)

## TABLE OF CONTENTS

<u>Section</u>	<u>Page No.</u>
DD 1423	
SUMMARY	3
TABLE OF CONTENTS	5
LIST OF ILLUSTRATIONS AND TABLES	8
I. INTRODUCTION	10
II. DEVICE	10
A. Description of Device	10
III. PROCESS AND FABRICATION IMPROVEMENTS INVESTIGATED	10
A. Ion Implantation	12
B. Webless Wicked	12
C. Tungsten Button - Convolutd	12
D. Tungsten Button - Nonconvolutd	12
E. Conclusion	12
IV. ELECTRICAL, MECHANICAL, THERMAL AND ENVIRONMENTAL INSPECTION CONFIRMATORY TEST PROGRAM	15
A. Group A Inspection	15
B. Group B Inspection	24
C. Group C Inspection	26
D. General Data	36
V. TEST EQUIPMENT	36
A. Surge Current Test Set	43
B. Forward On-State Voltage Test Set	46
C. Thermal Fatigue Test Set	46

<u>Section</u>	<u>Page No.</u>
V. TEST EQUIPMENT (Cont.)	
D. Blocking Current Test Set	46
E. Blocking Voltage Life Test	53
F. Thermal Resistance Test Set	53
VI. CONCLUSIONS AND RECOMMENDATIONS	56
VII. DISTRIBUTION LIST	59

# LIST OF ILLUSTRATIONS AND TABLES

<u>Figure No.</u>	<u>Title</u>	<u>Page No.</u>
1	Transcaltent Rectifier J15401 Cross Section	11
2	Cross Section Showing Webless Wick	13
3	Prefabricated Cathode (Emitter) Heat-Pipe	14
4	J15401 "Go-No-Go" Gauge	19
5	Reverse Current at +25°C	21
6	Thermal Resistance	21
7	Reverse Current at +125°C	25
8	Forward Voltage Drop	25
9	Post Surge Reverse Current	27
10	Reverse Recovery Time	27
11	Post Barometric Pressure Reverse Current	28
12	Post Blocking Voltage Reverse Current	28
13	Post Thermal Shock Reverse Current	31
14	Post Thermal Shock and Moisture Reverse Current	31
15	Post Salt Spray Reverse Current	32
16	Post Thermal Fatigue Reverse Current	32
17	Post Thermal Fatigue Thermal Impedance	34
18	Post Shock and Vibration Reverse Current	34
19	Post Shock and Vibration Thermal Resistance	35
20	Statistical Distribution of Dimension A	35
21	Statistical Distribution of Dimension B	41
22	Statistical Distribution of Dimension C	41
23	Statistical Distribution of Dimension D	42
24	Statistical Distribution of Dimension F	42



<u>Figure No.</u>	<u>Title</u>	<u>Page No.</u>
25	Repetitive Surge Current Test Set	44
26	Semiautomatic Multiple Surge Current Test Set - Block Diagram	45
27	Forward On-State Voltage Test Set	47
28	Forward On-State Test Set - Block Diagram	48
29	Thermal Fatigue Test Set	49
30	Thermal Fatigue Test Set - Block Diagram	50
31	Blocking Current Test Set	51
32	Reverse Blocking Current Test Set - Block Diagram	52
33	Blocking Voltage Life Test Set	54
34	Blocking Voltage Life Test Set - Block Diagram	55
35	Thermal Resistance Test Set	57
36	Thermal Resistance Test Set - Block Diagram	58

# TABLES

<u>Table No.</u>	<u>Title</u>	<u>Page No.</u>
1	Sample Size	16
2	Physical Dimensions of Confirmatory Samples	17
3	Statistical Analysis of Dimensional Data	18
4	Electrical Data	22
5	Initial and Final Thermal Resistance	23
6	Post Environmental Data	30
7	Statistical Analysis of Confirmatory Data	37
8	Key to Table 7	38
9	Electrical and Environmental Test Equipment	39

## I. INTRODUCTION

This report is the Interim Technical Report describing the work performed by RCA, Lancaster, PA during the confirmatory phase of the contract covering the period of 17 December 1978-22 October 1979. Work was performed in accordance with the DRDME-EA Purchase Description, dated 16 November, 1977 to the MERADCOM Semiconductor Device, Silicon Transcendent Rectifier Specification, dated 6 June 1978, as attached to the contract. The scope of the contract covers the MM&T tasks for fabricating a semiconductor device, silicon Transcendent rectifier, RCA type J15401 and the subsequent pilot production of the device.

Although this report covers the confirmatory phase of the program, the 24 months duration program will establish the production engineering techniques and verify a pilot production capability for the J15401 silicon Transcendent rectifier conforming to Fig. 1 of this report. Electrical, thermal and environmental inspections are a part of this report per DD 1423 of the contract.

## II. DEVICE

### A. Description of the Structure

The Transcendent rectifier type J15401 is thoroughly described in the report entitled, "Manufacturing Methods and Technology Measure for Fabrication of Silicon Transcendent Rectifier, Interim Technical Report, dated January 1979. The above report includes a Flow Diagram for the J15401 rectifier wafer metallizing, contouring and testing and a Flow Diagram for the assembly and processing of the J15401 rectifier. Included also are many step by step procedures utilized in the processes described. The report stipulated will serve as an aid to the understanding of this report, however, the cross section drawing of the Transcendent rectifier will conform to Fig. 1 of this report.

## III. PROCESS AND FABRICATION IMPROVEMENTS INVESTIGATED

All ten confirmatory sample rectifier devices were fabricated utilizing as much as possible the recommendations given in RCA proposal DP-8135 and the descriptions given in this report.

Four product design variations were tested in the confirmatory sample phase. However, the differences were slight as the outline or interface surfaces of the device remained the same and the performance characteristics were identical. Each variation was included as a possible production improvement consisting of the following items.




Figure 1 Transcaltent Rectifier Type J15401 Cross Section Drawing

#### A. Ion Implantation

Two units were successfully tested which were ion implanted with a boron  $N_{\text{dose}} = 6 \times 10^{15}$  at 200 KeV on one side and a phosphorus  $N_{\text{dose}} = 6.5 \times 10^{15}$  at 180 KeV on the other side. There was no detectable difference in electrical performance of the ion implanted vs. the standard process rectifiers. Ion implantation eliminated five of the nine process steps and substituted the two implants.

The ion implantation was investigated as a future production method. Unfortunately, the time for implanting with our equipment was 20 minutes per wafer for the boron side alone. One side of a wafer could be boron doped in 3.5 minutes with our standard procedures, and this time could easily be cut in half by doubling the wafer boat size. A hot source implanter could implant economically, but the contractor does not intend to buy one at the present time. Consequently, standard doped wafers will be used in the pilot run.

#### B. Webless Wicked

This concept is shown in Fig. 2. The anode portion of the cross section shows a webless wick. Conversely the cathode portion (ceramic side) displays a webbed wicked assembly. Eliminating the wick is a definite process improvement which helps to make the device more manufacturable. Consequently, this approach will be used in the pilot run.

#### C. Tungsten Button-Convolutated

The convoluted design was incorporated into the cathode heat-pipe to reduce low temperature stresses. Fig. 3 displays the convoluted concept. Test results indicate that the rectifier does not need the convolution at low temperatures which simplifies the construction of the part in question. Confidence was gained when two non-convoluted designs were tested down to  $-55^{\circ}\text{C}$  which is much more severe than the  $-25^{\circ}\text{C}$  test stipulated by the contract.


#### D. Tungsten Button - Nonconvoluted

This approach which can be seen in Fig. 2 has been adopted as the pilot run design for reasons discussed under C.

#### E. Conclusion

The design of the pilot run devices includes the outline of Fig. 1, standard doped wafers, webless wicks, and non-convoluted cathode strain sleeves. This combination of

Fig. 2 Cross Section Showing Webless Wick



SCALE  
DIMENSIONS IN

CAUTION: Use only the lubricants specified in E.S. 33-33-805  
UNLESS OTHERWISE SHOWN, DIMENSIONS SHOWN WITHOUT TOLERANCES ARE DESIGN CENTERS

98-1-78 110 DLY/AU

• CHANGE  
• ADDITION  
• DELETION

These drawings and specifications are the property of RCA Corporation, Electronic Components and shall not be reproduced or copied or used as the basis for the manufacture or sale of apparatus and or devices without permission

PL 309 10-78




Figure 3 Pre-Fabricated Cathode (Emitter) Heat-Pipe

features has been proven acceptable via the confirmatory tests and they will remain in force as part of the identity of the J15401 Transcalent silicon rectifier.

IV. ELECTRICAL, MECHANICAL, THERMAL AND ENVIRONMENTAL INSPECTION CONFIRMATORY TEST PROGRAM

Ten silicon rectifiers were tested during the Confirmatory Sample phase of this program. The total sample consisted of four variations. The serial numbers and corresponding construction variations were as follows:

<u>Ser. No.</u>	<u>Variation</u>
II-2	Ion Implanted
II-3	
J149	Webless Wicked
J150	
J151	
J157	Tungsten Button: Convolutud
J160	
J162	
J156	Tungsten Button: Nonconvolutud
J163	

Due to the variations in construction, the number of units subjected to each environmental test was equal to or greater than the sample size listed in the confirmatory test plan previously issued. Table 1 lists the plan's sample size and the actual number of devices tested. In addition, it lists the permitted percentage of failures.

A. Group A Inspection

1. Subgroup 1

All of the Transcalent rectifiers were visually and mechanically inspected in conformance to method 2071 and Fig. 1 of the specification as modified by the Interim Engineering Report dated January 1979 using the specified method 2066. The actual measurements of the ten confirmatory J15401C rectifiers are listed in Table 2. Table 3 shows the results of a statistical analysis of these data which indicate that all of the devices met the specified dimensions with margin.

In addition to taking actual measurements all the devices were checked using the "go-no-go" gauge shown in Fig. 4.



TABLE 1

Sample Size

Subgroup No.	Title	% of Units To Be Tested	Actual % of Units Tested	% Allowed To Fail	Actual % Failed
1	Barometric Pressure Reduced	50	100	0	0
2	Blocking Voltage L.T.	30	100	0	0
3	Thermal Shock	20	100	0	0
	Moisture Resistance	20	20	0	0
	Salt Atmosphere	20	20	0	0
4	Thermal Fatigue	100	100	10	0
5	Shock	20	50	0	0
	Vibration, Variable Freq.	20	50	0	0

Table 2

## Physical Dimensions of Confirmatory Samples

<u>Device</u> <u>#</u>	<u>A</u>	<u>B</u>	<u>C</u>	<u>D</u>	<u>F</u>
II2	4.761	3.456	0.640	1.808	2.100
II3	4.761	3.464	0.650	1.834	2.100
J149	4.737	3.447	0.635	1.800	2.104
J150	4.751	3.463	0.647	1.806	2.101
J151	4.744	3.455	0.641	1.805	2.100
J156	4.748	3.476	0.624	1.800	2.100
J157	4.723	3.465	0.632	1.790	2.102
J160	4.749	3.472	0.631	1.792	2.106
J162	4.748	3.472	0.628	1.804	2.102
J163	4.718	3.463	0.635	1.803	2.100

Table 3

Statistical Analysis of the Dimensional Data  
of the Confirmatory Samples

<u>Character</u>	<u>Avg.</u>	<u>Sigma</u>	<u>Max.</u>	<u>Min.</u>	<u>Chi-Sq.</u>	<u>N</u>
Dim. A	4.744	0.014	4.761	4.718	8.38	10
Dim. B	3.463	0.009	3.476	3.447	2.95	10
Dim. C	0.636	0.008	0.650	0.624	3.82	10
Dim. D	1.804	0.012	1.834	1.790	12.40	10
Dim. F	2.102	0.002	2.106	2.100	15.21	10




Fig. 4 J15401 "Go-No-Go" Gauge

2. Subgroup 2 - Test Temperature  $T_A = 25 \pm 3^\circ\text{C}$

All confirmatory samples were tested for reverse current,  $i_r$ , and reverse voltage,  $V_r$ , under the conditions specified for method 4016.2. Fig. 5 is a histogram of the reverse current measured under the conditions in the specification. Table 4 lists the detail data.

From the statistical data we can expect all of the measurements to be less than 1.2 mA or 8% of the specified 15 mA maximum.

Prior to submitting the devices to electrical test they all were tested out to 1000 volts of reverse voltage to insure that a sufficient safety margin existed.

3. Subgroup 3 - Thermal Resistance

The thermal resistance of the Transcalent rectifiers was measured using the specified method described in paragraph 4.6.1 of the specification. Each rectifier was calibrated for a temperature dependent parameter by recording the forward voltage drop at 4 amperes at several temperatures. The thermal resistance ( $R_{\theta JC}$ ) was tested at 250 amperes of heating current, interrupted by a short period of time (less than 1 msec.) when the current was reduced to the metering value of 4 amperes. The forward voltage drop across the device was measured and used to determine the junction temperature from the calibration data. Simultaneously, the external temperature of the heat-pipes was measured and recorded. The difference in temperatures divided by the input heating power is the thermal impedance (transient) or resistance (steady state) of the device. The values of thermal resistance calculated from the data measured on the ten confirmatory samples are shown in Table 4. Fig. 6 is a histogram of these data. Thermal resistance calculated on the same devices after the environmental tests are listed in Table 5 with the initial values for comparison.

No. of Devices

# HISTOGRAM DATA(1)

LOWER CELL LIMIT,CELL WIDTH AND NUMBER OF CELLS :.5 .02 25

VERT SCALE:1

CHAR:IR+25 C

CHARACTERISTIC-IR+25 C

AVERAGE- 0.822

SIGMA--- 0.1250599856

MAXIMUM- 0.92

MINIMUM- 0.61

SAMPLE-- 10

Limit

15 mA Max.




Fig. 5 Reverse Current at +25°C, (mA)

No. of Devices

## Histogram Data (3)

LOWER CELL LIMIT,CELL WIDTH AND NUMBER OF CELLS :.03 .02 25

VERT SCALE:1

CHAR:RΘJC

CHARACTERISTIC-RΘJC

AVERAGE- 0.114

SIGMA--- 0.04718756898

MAXIMUM- 0.2

MINIMUM- 0.07

SAMPLE-- 10

Limit

0.2°C/W




Fig. 6 Thermal Resistance, R<sub>θJC</sub> (°C/W)

TABLE 4

Date 9/5/79

## Confirmatory Samples

Tester P. Bransby

## Electrical Data

Method Symbol	Visual	Dimensions	+25°C Rev. Cur. and Rev. Voltage	Thermal Resistance for Rect. Diode	+125°C Rev. Current and Rev. Voltage	Forward Voltage	Post Surge Current Test	Reverse Recovery Time	Post Barometric Pressure
Units	2071	2066	4016.2 $i_r$ mA	Para. 4.6.1 $R_{\theta JC}$ °C/W	4016.2 $i_r$ mA	4011.3 $V_f$ Volts	4066.2 $i_r$ mA	4031 $t_{rr}$ usec.	1001.1 $i_r$ mA
Ser. No.									
J149	✓	✓	0.81	0.10	1.75	1.0	0.72	2.8	0.72
J150	✓	✓	0.61	0.11	1.80	1.0	0.51	2.6	0.72
J151	✓	✓	0.77	0.11	4.12	1.0	0.61	2.8	0.72
J156	✓	✓	0.92	0.07	6.18	0.92	0.72	2.4	0.68
J157	✓	✓	0.92	0.09	5.36	0.98	0.82	2.9	0.72
J160	✓	✓	0.92	0.08	2.06	0.98	0.82	3.0	0.72
J162	✓	✓	0.82	0.08	2.57	1.0	0.82	3.2	0.72
J163	✓	✓	0.92	0.20	1.85	1.0	0.82	2.9	0.69
II-2	✓	✓	0.61	0.10	1.44	1.0	0.61	2.4	0.33
II-3	✓	✓	0.92	0.20	1.44	1.0	0.67	2.0	0.29
Spec.			15 Max.	0.2 Max.	60 Max.	2.0 Max.	15 Max.	15.0 Max.	15 Max.

Table 5  
Initial and Final Thermal Resistance  
 $^{\circ}\text{C}/\text{W}$

Ser. No.	$T_A = 25 \pm 3^{\circ}\text{C}$										Max. Spec. $^{\circ}\text{C}/\text{W}$
	J149	J150	J151	J156	J157	J160	J162	J163	II2	II3	
Initial	0.1	0.11	0.11	0.07	0.09	0.08	0.08	0.2	0.1	0.2	0.2
Final	0.13	0.10	0.16	0.14	0.10	0.1	0.09	0.15	0.2	0.19	0.2



Two of the devices, J12 (ion implanted) and J163 (nonconvoluted), had initial Thermal Impedance measurements at the upper limit of the specification,  $0.2^{\circ}\text{C/W}$ . Since similarly constructed devices in the confirmatory sample, J1-2 and J156, had initial normal measurements of  $0.1^{\circ}\text{C/W}$  and  $0.07^{\circ}\text{C/W}$  respectively, it is not believed that the high measurements are construction orientated, but rather a normal variation.

4. Subgroup 4 - Test Temperature of Case:  $125 \pm 6^{\circ}\text{C}$   
Reverse Current,  $i_r$ , and Reverse Voltage,  $V_r$

The devices were tested under the specified conditions by method 4016.2. The specification limit for maximum peak current is 60 mA. The detail data measured is listed in Table 4. Fig. 7 is a histogram of the distribution of the  $i_r$  measured at a reverse voltage of 800 V. These data indicate that all the devices were well within the maximum limits specified.

#### B. Group B Inspection

1. Subgroup 1 - Forward Voltage,  $V_f$ : Test at Room Ambient Temperature of  $25 \pm 3^{\circ}\text{C}$

The peak forward voltage drop was measured across all of the devices using method 4011.3. The devices were conducting an average current of 250 amperes when the measurements were made. Since the current conducted by the device is nearly  $180^{\circ}$  of conduction angle, the peak current is approximately 800 amperes and the RMS current is about 400 amperes.

During the tests, the Transcalent rectifiers were allowed to reach thermal equilibrium and the heat-pipe was confirmed to be isothermal. Room ambient air was blown across the fins to limit the temperature of the heat-pipes to  $100^{\circ}\text{C}$ .

The individual data are listed in Table 4 and the distribution is shown in Fig. 8. All devices passed.



2. Subgroup 2 - Surge Current,  $i_f$   
Test Temperature,  $T_A = 25 \pm 3^\circ\text{C}$

All confirmatory samples were tested under the conditions listed in the specification using method 4066.2. The surge current test was performed in the RCA owned test circuit that was developed for the J15371 Transcendent thyristor under Contract No. DAAB07-76-C-8120 and modified to test the rectifiers. The pulses of surge current were repeated at a rate of one pulse per minute for ten total surges. The 800 volts of reverse voltage,  $V_r$ , was reapplied following each surge. After the surge test, the reverse current was remeasured to confirm that the 4000 amperes peak surge currents did not damage the devices.

The values of reverse current measured after this surge test are listed in Table 4 and the distribution is plotted in Fig. 9. Comparing these data with those measured initially (reverse current -  $25^\circ\text{C}$ ) indicated the confirmatory samples were not affected by the surge test.

3. Subgroup 3 - Reverse Recovery Time,  $T_{rr}$   
Test Temperature  $T_A = 25 \pm 3^\circ\text{C}$

All devices were tested for reverse recovery time per the procedures of method 4031 of MIL-Std-750B. A modified circuit as outlined in the JEDEC Publication No. RS282 was used. This circuit utilizes the circuit parameters specified, however, the  $I_{FM}$  is standardized at 125 instead of 50 peak amperes.

The data measured on the engineering samples are listed in Table 4 and the distribution shown in Fig. 10. Again, the devices passed with margin.

#### C. Group C Inspection

1. Subgroup 1 - Barometric Pressure Reduced

All of the confirmatory devices were successfully tested under the conditions listed using the specified method 1001.1. A device which arcs over or exhibits harmful coronas that deteriorate the device is considered a failure. After exposure to the low pressure test the devices were tested for reverse current per Subgroup 2 of Table 1. The detail data is listed in Table 4 and the distribution plotted in Fig. 11.

# Histogram Data (6)

No. of Devices

LOWER CELL LIMIT, CELL WIDTH AND NUMBER OF CELLS : .45 .05 25  
VERT SCALE: 1

CHAR: POST SURGE IR

CHARACTERISTIC: POST SURGE IR

AVERAGE-- 0.712  
SIGMA--- 0.1106345385  
MAXIMUM-- 0.82  
MINIMUM-- 0.51  
SAMPLE--- 10

Limit  
15 mA Max.

```

4+      □
3+      □
2+    □ □ □
1+  □ □ □ □ □
+++++
0 0 0 0 0 0 1 1 1 1 1 1 1
. . . . .
4 5 6 7 8 9 0 1 2 3 4 5 6
5 5 5 5 5 5 5 5 5 5 5 5 5
  
```

Fig. 9 Post Surge Reverse Current,  $I_r$  , (mA)

## HISTOGRAM DATA: 51

LOWER CELL LIMIT, CELL WIDTH AND NUMBER OF CELLS : 1.2 .06 25  
VERT SCALE: 1

CHAR: TRR

CHARACTERISTIC: TRR

AVERAGE 2.7  
SIGMA--- 0.9527668415  
MAXIMUM-- 3.2  
MINIMUM-- 2  
SAMPLE--- 10

Limit  
15  $\mu$ sec. Max.

```

2+      □      □ □
1+  □      □ □ □ □ □
+++++
1 2 2 2 2 2 2 2 2 3 3 3
. . . . .
7 0 1 2 3 5 6 7 8 9 1 2 3
2 4 6 8 2 4 6 8 2 4
  
```

Fig. 10 Reverse Recovery Time,  $T_{rr}$  ( $\mu$ sec)

No. of Devices

# HISTOGRAM DATA[;7]

LOWER CELL LIMIT, CELL WIDTH AND NUMBER OF CELLS : .20 .05 25

VERT SCALE: 1

CHAR: POST BARO IR

CHARACTERISTIC-POST BARO IR

AVERAGE- 0.631

SIGMA--- 0.1700620802

MAXIMUM- 0.72

MINIMUM- 0.29

SAMPLE--- 10

Limit  
15 mA Max.

6+		□
5+		□
4+		□
3+		□
2+		□□
1+	□□	□□

+++++

0	0	0	0	0	0	0	0	0	1	1	1	1	1
.	.	.	.	.	.	.	.	.	.	.	.	.	.
2	3	4	5	6	7	8	9		1	2	3	4	

Fig. 11 Post Barometric Pressure Reverse Current,  $I_r$  (mA)

No. of Devices

# HISTOGRAM DATA[;8]

LOWER CELL LIMIT, CELL WIDTH AND NUMBER OF CELLS : .04 .05 25

VERT SCALE: 1

CHAR: POST BVLT IR

CHARACTERISTIC-POST BVLT IR

AVERAGE- 0.654

SIGMA--- 0.1024369725

MAXIMUM- 0.72

MINIMUM- 0.46

SAMPLE--- 10

Limit  
15 mA Max.

8+														□
7+														□
6+														□
5+														□
4+														□
3+														□
2+														□□
1+														□□

+++++

0	0	0	0	0	0	0	0	0	0	0	1	1	1
.	.	.	.	.	.	.	.	.	.	.	.	.	.
0	1	2	3	4	5	6	7	8	9	0	1	2	
4	4	4	4	4	4	4	4	4	4	4	4	4	4

Fig. 12 Post Blocking Voltage Reverse Current,  $I_r$  (mA)

2. Subgroup 2 - Blocking Voltage Life Test Temperature:  $T_C = 125 \pm 6^\circ\text{C}$

All of the confirmatory devices were tested for 200 hours, each under the conditions specified, using the method of para. 4.6.2. After exposure to the blocking voltage life test, the reverse current was measured and recorded. The detail data measured is listed in Table 6 and the distribution of the data plotted in Fig. 12. All devices passed with margin.

The test plan required that only three devices be tested for this parameter. Since four different types of devices made up the samples (see Sec. IV) it was decided that all ten devices should be tested for this parameter for a complete evaluation.

3. Subgroup 3 - Thermal Shock, Moisture Resistance and Salt Atmosphere Tests

All the confirmatory devices were tested for Thermal Shock using test method 1051.1 and the conditions stated in the specification. After five cycles, the rectifiers were removed from the environmental chamber and two were submitted to the Moisture Resistance test, method 1021.1.

Reverse current measurements per Subgroup 2 of Table 1 of the specifications were taken as a check at this point to determine if the devices had survived the Thermal Shock and Moisture Resistance tests. All the units passed. Detail data is listed in Table 6 and the distributions plotted in Figs. 13 and 14.

The two devices (II2, II3) which had been subjected to the Moisture Test were subjected to the Salt Atmosphere test method 1041.1 for 24 hours. After the test, the salt was washed off of the devices which were then examined. The markings were legible and there was no evidence of flaking, pitting of the finish, or corrosion that would interfere with the application of the devices.

Reverse current tests per Subgroup 2 of Table 1 of the specification were performed, the detail data are listed in Table 6 and the distribution is plotted in Fig. 15. All devices passed with margin.

TABLE 6

Date 8/29/79

## Post Environmental Data

Tester P. Bransby

Method	Par. 4.6.2	1051.1	Post Thermal Shock and Moisture Test	1021.1 1051.1	Post Salt Spray Test	2016.2, 2056	Post Shock and Vibration Test	Par. 4.6.3	Post Thermal Fatigue Resistance Test	Par. 4.6.1	Post Thermal Fatigue Thermal Resistance Test	Final Envir. Thermal Resistance Test
Symbol	$i_r$	$i_r$	$i_r$	$i_r$	$i_r$	$i_r$	$i_r$	$i_r$	$R_{\theta jc}$	$R_{\theta jc}$	$R_{\theta jc}$	$R_{\theta jc}$
Units	mA	mA	mA	mA	mA	mA	mA	mA	OC/W	OC/W	OC/W	OC/W
<u>Ser. No.</u>												
J149	0.70	0.69	--	--	--	--	--	0.70	0.13	--	--	--
J150	0.70	0.69	--	--	--	--	--	0.70	0.10	--	--	--
J151	0.70	0.61	--	--	--	0.72	0.70	0.70	0.12	0.16	0.16	0.16
J156	0.70	0.60	--	--	--	0.67	0.57	0.57	0.14	0.14	0.14	0.14
J157	0.72	0.50	--	--	--	0.74	0.70	0.70	0.098	0.10	0.10	0.10
J160	0.70	0.50	--	--	--	--	0.70	0.70	0.10	--	--	--
J162	0.70	0.60	--	--	--	--	0.78	0.78	0.09	--	--	--
J163	0.70	0.50	--	--	--	--	0.72	0.72	0.15	--	--	--
II2	0.46	--	0.41	0.41	0.41	0.46	0.56	0.56	0.2	--	--	--
II3	0.46	--	0.41	0.41	0.41	0.46	0.56	0.56	0.19	--	--	--
Spec.	15 (Max.)	15 (Max.)	15 (Max.)	15 (Max.)	15 (Max.)	15 (Max.)	15 (Max.)	15 (Max.)	0.2 (Max.)	0.2 (Max.)	0.2 (Max.)	0.2 (Max.)

Histogram Data (9)

LOWER CELL LIMIT, CELL WIDTH AND NUMBER OF CELLS : .40 .02 25  
VERT SCALE: 1

CHAR: POST THER SH

CHARACTERISTIC- POST THER SH

AVERAGE- 0.58625

SIGMA--- 0.07998888851

MAXIMUM- 0.69

MINIMUM- 0.5

SAMPLE-- 8

Limit  
15 mA Max.

3+    □    □  
2+    □    □    □  
1+    □    □    □  
+++++  
0 0 0 0 0 0 0 0 0 0 0 0 0  
.  
4 4 4 5 5 6 6 6 7 7 8 8 8  
4 8 2 6    4 8 2 6    4 8

No. of Devices

Fig. 13 Post Thermal Shock Reverse Current,  $I_r$  (mA)

Histogram Data (10)

~~LOWER CELL LIMIT, CELL WIDTH AND NUMBER OF CELLS : .35 .02 25~~  
~~VERT SCALE: 1~~

~~CHAR: TH SH MO~~

~~CHARACTERISTIC- TH SH MO~~

~~AVERAGE- 0.41~~

~~SIGMA--- 0~~

~~MAXIMUM- 0.41~~

~~MINIMUM- 0.41~~

~~SAMPLE-- 2~~

Limit  
15 mA Max.

2+    □  
1+    □  
+++++  
0 0 0 0 0 0 0 0 0 0 0 0 0  
.  
~~3 3 4 4 5 5 5 6 6 7 7 7 8~~  
~~5 9 3 7 1 5 9 3 7 1 5 9 3~~

No. of Devices

Fig. 14 Post Thermal Shock and Moisture Reverse Current,  $I_r$  (mA)



# Histogram Data (11)

LOWER CELL LIMIT, CELL WIDTH AND NUMBER OF CELLS : .35 .01 25  
VERT SCALE: 1

CHAR: POST SALT SP

CHARACTERISTIC-POST SALT SP

AVERAGE- 0.41  
SIGMA- 0  
MAXIMUM- 0.41  
MINIMUM- 0.41  
SAMPLE- 2

Limit  
15 mA Max.

No. of Devices

```

2+      □
1+      □
+++++
0 0 0 0 0 0 0 0 0 0 0 0 0 0
 3 3 3 4 4 4 4 4 5 5 5 5 5
 5 7 9 1 3 5 7 9 1 3 5 7 9
    
```

Fig. 15 Post Salt Spray Reverse Current,  $I_r$  (mA)

## HISTOGRAM DATA[13]

LOWER CELL LIMIT, CELL WIDTH AND NUMBER OF CELLS : .45 .05 25  
VERT SCALE: 1

CHAR: POST TH FRT

CHARACTERISTIC-POST TH FRT

AVERAGE- 0.669  
SIGMA- 0.0769487564  
MAXIMUM- 0.78  
MINIMUM- 0.56  
SAMPLE- 10

Limit  
15 mA Max.

No. of Devices

```

6+      □
5+      □
4+      □
3+      □ □
2+      □ □
1+      □ □□
+++++
0 0 0 0 0 0 1 1 1 1 1 1 1
 4 5 6 7 8 9 0 1 2 3 4 5 6
 5 5 5 5 5 5 5 5 5 5 5 5 5
    
```

Fig. 16 Post Thermal Fatigue Reverse Current,  $I_r$  (mA)

#### 4. Subgroup 4 - Thermal Fatigue Test

All of the confirmatory samples were tested for reliability under the specified Thermal Fatigue Test Conditions and Spec. paragraph 4.6.3. The "on" and "off" times were two minutes each. The air flow across the devices was adjusted so that when the devices were conducting, the case or heat-pipe temperature was  $90 \pm 10^\circ\text{C}$  max. and  $30 \pm 10^\circ\text{C}$  min. The devices were subjected to a minimum of 200 "on-off" cycles. Ten measurements per Subgroup 2 of Table 1 were made. Detail data are listed in Table 6 and distribution is plotted in Fig. 16.

Since the sample consisted of four different constructions, an additional post thermal fatigue parameter was measured, Thermal Impedance. These data are listed in Table 6 and the distribution is plotted in Fig. 17.

All devices passed. The ion-implanted devices came closest to the specification limit of  $0.2^\circ\text{C/W}$ . Because of this high thermal impedance and other considerations, ion-implanted devices will not be used in the pilot run of this MM&T contract.

#### 5. Subgroup 5 - Shock & Vibration Tests

Five of the confirmatory samples were shock tested in RCA's Environmental Laboratory, Lancaster, PA using the specified conditions and test method 2016.2.

Following the shock tests, all devices were subjected to a vibration test of variable frequency described in the Specification and Test Method 2056. After the shock and vibration tests, the reverse current measurements at 800 volts and the thermal resistance measurements of Subgroups 2 and 3 of Table 1 were repeated successfully to verify the integrity of the devices. Detail data are listed in Table 6 and the distributions are plotted in Figs. 18 and 19.

The Acceptance Test Procedure required that only two devices be subjected to the Shock and Vibration Tests. Since four different constructions were represented in the sample, RCA subjected a sample of each to the environmental test as follows:

No. of Devices

# HISTOGRAM DATA[;14]

LOWER CELL LIMIT,CELL WIDTH AND NUMBER OF CELLS :.07 .03 25  
VERT SCALE:1

CHAR:POST ENVR RΘJC

CHARACTERISTIC-POST ENVR RΘJC

AVERAGE- 0.1318

SIGMA--- 0.03871778231

MAXIMUM- 0.2

MINIMUM- 0.09

SAMPLE--- 10




Fig. 17 Post Thermal Fatigue Thermal Impedance (°C/W)

No. of Devices

## Histogram Data (12)

LOWER CELL LIMIT,CELL WIDTH AND NUMBER OF CELLS :.40 .05 25  
VERT SCALE:1

CHAR:SH VIR

CHARACTERISTIC-SH VIR

AVERAGE- 0.61

SIGMA--- 0.1392838828

MAXIMUM- 0.74

MINIMUM- 0.46

SAMPLE--- 5




Fig. 18 Post Shock and Vibration Reverse Current, I<sub>r</sub> (mA)

Histogram Data (15)

LOWER CELL LIMIT, CELL WIDTH AND NUMBER OF CELLS : .08 .02 25

VERT SCALE: 1

CHAR: FIN ENVR  $R_{\theta JC}$

CHARACTERISTIC- FIN ENVR  $R_{\theta JC}$

AVERAGE- 0.133333333

SIGMA--- 0.08055050463

MAXIMUM- 0.16

MINIMUM- 0.1

SAMPLE--- 3

Limit  
0.2°C/W Max.

No. of Devices

```

1+ 0 00 |
+++++
0 0 0 0 0 0 0 0 0 0 0 0 0
. . . . .
0 1 1 2 2 2 3 3 4 4 4 5 5
3 2 6 4 8 2 6 4 8 2 6
  
```

Fig. 19 Post Shock and Vibration Thermal Resistance,  $R_{\theta JC}$  (°C/W)

HISTOGRAM DATA[16]

LOWER CELL LIMIT, CELL WIDTH AND NUMBER OF CELLS : 3.5 .5 25

VERT SCALE: 1

CHAR: DIM A

CHARACTERISTIC- DIM A

AVERAGE- 4.744

SIGMA--- 0.01433720878

MAXIMUM- 4.761

MINIMUM- 4.718

SAMPLE--- 10

No. of Devices

```

10+ 0
9+ 0
8+ 0
7+ 0
6+ 0
5+ 0
4+ 0
3+ 0
2+ 0
1+ 0
+++++
3 4 5 6 7 8 9 1 1 1 1 1 1
. . . . . 0 1 2 3 4 5
5 5 5 5 5 5 5 . . . . .
5 5 5 5 5 5
  
```

Fig. 20 Statistical Distribution of Dimension A

<u>No. of Devices</u>	<u>Construction</u>
1	Webless Wicked
1	Convolute Tungsten Button
1	Nonconvolute Tungsten Button
2	Ion-Implanted

Again all devices passed. The Thermal Resistance data listed for II2 and II3 were measured after the Shock and Vibration Tests.

#### D. General Data

Table 7 lists a statistical analysis of all the data measured during this confirmatory test. Table 8 lists the key for identifying the individual characteristics. Figs. 20, 21, 22, 23 and 24 show the distribution of the dimensions of the samples.

In addition to the tests discussed, two nonconvoluted devices with tungsten buttons were subjected to two complete thermal shock tests using method 1051.1 and a low temperature of  $-55^{\circ}\text{C}$  instead of the specified  $-25^{\circ}\text{C}$ . This action results in doubling the number of nonconvoluted tested doubling the number of cycles to 10 instead of 5, and doubling the stress to  $-55^{\circ}\text{C}$  instead of  $-25^{\circ}\text{C}$ . Both devices passed with flying colors.

<u>S/N</u>	<u>Reverse Current (<math>I_r</math>) mA</u>	<u>Thermal Resistance (<math>R_{\theta JC}</math>) <math>^{\circ}\text{C}/\text{W}</math></u>	
J155	0.82	0.1	initial data
	0.1	0.15	after test
J158	0.87	0.09	initial data
	0.1	0.12	after test

#### V. TEST EQUIPMENT

Refer to the First through Sixth Monthly Reports for this contract for additional information concerning test apparatus. The electrical and environmental test equipment survey listed in the Interim Report for the Engineering Samples repeated and updated here for reference in Table 9.

Table 7

## Statistical Analysis of Confirmatory Data

PRODUCT-----CONFIRMATORY SILICON TRANSCALENT RECTIFIER DATA							
CHARACTERISTIC	AVG	SIGMA	MAX	MIN	CHI-SQ	N	
1	.822	.125	.920	.610	21.20	10	
2	2.857	1.732	6.180	1.440	12.85	10	
3	.114	.047	.200	.070	18.89	10	
4	.988	.025	1.000	.920	19.69	10	
5	2.700	.353	3.200	2.000	4.71	10	
6	.712	.111	.820	.510	8.26	10	
7	.631	.170	.720	.290	23.41	10	
8	.654	.102	.720	.460	26.26	10	
9	.586	.080	.690	.500	16.37	8	
10	.410		.410	.410	2.00	2	
11	.410		.410	.410	2.00	2	
12	.610	.139	.740	.460	9.71	5	
13	.669	.077	.780	.560	14.74	10	
14	.132	.039	.200	.090	11.12	10	
15	.133	.031	.160	.100	4.30	3	
16	4.744	.014	4.761	4.718	8.38	10	
17	3.463	.009	3.476	3.447	2.95	10	
18	.636	.008	.650	.624	3.82	10	
19	1.804	.012	1.834	1.790	12.40	10	
20	2.102	.002	2.106	2.100	15.21	10	

TUESDAY, OCTOBER 9, 1979

Table 8

## Key to Statistical Analysis of Table 7

Characteristic #	<u>Definition</u>
1	Reverse Current ( $I_R$ ) at +25°C
2	Reverse Current ( $I_R$ ) at +125°C
3	Thermal Impedance $R_{\theta JC}$
4	Forward Voltage ( $V_{FM}$ )
5	Reverse Recovery Time ( $T_{RR}$ )
6	Post Surge Test, Reverse Current ( $I_R$ )
7	Post Barometric Test, Reverse Current ( $I_R$ )
8	Post Blocking Voltage Life Test, Reverse Current ( $I_R$ )
9	Post Thermal Shock Test, Reverse Current ( $I_R$ )
10	Post Thermal Shock & Moisture Test, Reverse Current ( $I_R$ )
11	Post Salt Spray Test. Reverse Current ( $I_R$ )
12	Post Shock & Vibration Test, Reverse Current ( $I_R$ )
13	Post Thermal Fatigue Test, Reverse Current ( $I_R$ )
14	Post Environmental Test, Thermal Resistance ( $R_{\theta JC}$ )
15	Final Environmental Test, Thermal Resistance ( $R_{\theta JC}$ )
16	Dimension A
17	Dimension B
18	Dimension C
19	Dimension D
20	Dimension F

TABLE 9  
ELECTRICAL AND ENVIRONMENTAL TEST EQUIPMENT

<u>Method</u>	<u>Test Description</u>	<u>Status of Facility</u>
2066	Physical Dimensions	Precision Vernier Calipers and "go-no-go" gauge available.
4016.2	Reverse Current	Facilities available for A.C. Method. Temperature Controlled Oven available.
Par. 4.6.1	Thermal Resistance	Engineering Test Facility available.
4011.3	Forward Voltage	Power Supply and Monitoring available.
4066.2	Surge Current	Surge Fwd. Current and Rev. Voltage Supplies are available.
4031	Reverse Recovery Time	JEDEC Test Circuit developed and test results correlate with RCA, Somerville, NJ, test data. Test equipment is operational.
1001.1	Barometric Pressure (reduced)	Vacuum Chamber and $V_r$ Supply available. Supply modified for half-wave operation.
Par. 4.6.2	Blocking-Voltage Life Test	Oven and Supply are available. Supply modified for half-wave operation.
1051.1	Thermal Shock (Temperature Cycling)	Test facility available at RCA, Lancaster, Environmental Test Laboratory.
1021.1	Moisture Resistance	Ditto
2016.2	Shock	Ditto
2056	Vibration, Variable Frequencies	Ditto



TABLE 9 (Cont.)

ELECTRICAL AND ENVIRONMENTAL TEST EQUIPMENT

<u>Method</u>	<u>Test Description</u>	<u>Status of Facility</u>
1041.1	Salt Atmosphere (corrosion)	Test facility available at RCA, Lancaster, Environmental Test Laboratory.
Par. 4.6.3	Thermal Fatigue Test	Power Supply and Controller are available.

DRT 9/22/78  
MFD 1/10/79  
MFD 9/25/79

No. of Devices

# HISTOGRAM DATA[;17]

LOWER CELL LIMIT, CELL WIDTH AND NUMBER OF CELLS :1.5 .5 25

VERT SCALE:1

CHAR: DIM B

CHARACTERISTIC-DIM B

AVERAGE- 3.4633

SIGMA--- 0.008844960901

MAXIMUM- 3.476

MINIMUM- 3.447

SAMPLE--- 10




Fig. 21 Statistical Distribution of Dimension B

# HISTOGRAM DATA[;18]

LOWER CELL LIMIT, CELL WIDTH AND NUMBER OF CELLS :.45 .05 25

VERT SCALE:1

CHAR: DIM C

CHARACTERISTIC-DIM C

AVERAGE- 0.6363

SIGMA--- 0.008219894565

MAXIMUM- 0.65

MINIMUM- 0.624

SAMPLE--- 10

No. of Devices




Fig. 22 Statistical Distribution of Dimension C

No. of Devices

HISTOGRAM DATA;191  
 LOWER CELL LIMIT,CELL WIDTH AND NUMBER OF CELLS :.5 .3 25  
 VERT SCALE:1  
 CHAR:DIM D

CHARACTERISTIC-DIM D  
 AVERAGE- 1.8042  
 SIGMA--- 0.01198888374  
 MAXIMUM- 1.834  
 MINIMUM- 1.79  
 SAMPLE-- 10

8+	□
7+	□
6+	□
5+	□
4+	□
3+	□
2+	□□
1+	□□

+++++

0	1	1	2	2	3	4	4	5	5	6	7	7
.	.	.	.	.	.	.	.	.	.	.	.	.
5	1	7	3	9	5	1	7	3	9	5	1	7

Fig. 23 Statistical Distribution of Dimension D

No. of Devices

HISTOGRAM DATA;201  
 LOWER CELL LIMIT,CELL WIDTH AND NUMBER OF CELLS :1.5 .1 25  
 VERT SCALE:1  
 CHAR:DIM F

CHARACTERISTIC-DIM F  
 AVERAGE- 2.1015  
 SIGMA--- 0.002068278941  
 MAXIMUM- 2.106  
 MINIMUM- 2.1  
 SAMPLE-- 10

10+	□
9+	□
8+	□
7+	□
6+	□
5+	□
4+	□
3+	□
2+	□
1+	□

+++++

1	1	1	2	2	2	2	2	3	3	3	3	3
.	.	.	.	.	.	.	.	.	.	.	.	.
5	7	9	1	3	5	7	9	1	3	5	7	9

Fig. 24 Statistical Distribution of Dimension F

#### A Surge Current Test Set

The surge current test is a survival test which demonstrates that a rectifier is capable of conducting unusually large amounts of current without being destroyed. In the surge test, there are four distinct, sequential circuit functions:

Application of 250 amperes average (400 amperes RMS) of "on" state heating current to bring the rectifier junction to its normal operating temperature,

Application of one 60 Hz, positive, 1/2 cycle high current surge to the DUT,

Application of one 60 Hz, negative, 1/2 cycle reverse high voltage pulse to the DUT.

The above test sequence of operations is repeated at one minute intervals for 10 total surges.

The repetitive surge current test is shown in Fig. 25. The circuit block diagram is illustrated in Fig. 26. Three power supplies are also involved in this test of DUT's ability to withstand overloads. Sequencing on the exact half or full 60 Hz cycle is designed into the equipment. High voltage interlocks are used for safety of the operating personnel.

An a.c. heating current supply heats the DUT to its normal operating temperature before a second supply applies a single, half cycle forward current surge to the DUT. On the subsequent half cycle, an 800 volts peak reverse a.c. voltage is applied to test whether the device has retained its blocking capability following the surge. This surge sequence is repeated ten times at one minute intervals. All pulse times are recorded temporarily on a storage oscilloscope for accurate readings.

Other test conditions, such as higher peak surges, lower reverse voltages and different time intervals can be set up, if desired. Forced air cooling is utilized.




Figure 25 Repetitive Surge Current  
Test Set. The DUT was mounted  
inside the interlocked door on  
the left in the photograph.



100

#### B. Forward On-State Voltage Test Set

In the forward on-state voltage test the peak forward voltage drop is measured while the rectifier is conducting its rated current. At the same time the operation of the heat-pipes is confirmed.

The test set shown in Fig. 27 applies the full rated average a.c. current to the DUT. The cooling air flow is adjusted to achieve the required  $100^{\circ}\text{C}$  on the case of the heat-pipe of the DUT before the peak forward voltage is read on the oscilloscope. A functional block diagram of the circuit is shown in Fig. 28.

During this test the temperature is measured at several points along the heat-pipes. In this way, the heat-pipes' thermal balance and isothermal characteristics can be verified. A poorly functioning heat-pipe is not isothermal. Properly functioning heat-pipes are important not only for the reliability of the DUT, but also because the on-state voltage is a function of the junction temperature.

#### C. Thermal Fatigue Test Set

Rectifiers are temperature cycled by operating them in a circuit in which the devices are heated by conducting their full rated current of 250 A average and cooled by blowing room temperature air across the fins on the device. The test is conducted for a minimum of 200 cycles. The test set is shown in Fig. 29 along with the functional block diagram of the circuit in Fig. 30. The air flow is adjustable to assure that the specified minimum and maximum (min.  $T_c = 30 \pm 10^{\circ}\text{C}$ , max.  $T_c = 90 \pm 10^{\circ}\text{C}$ ) temperatures are achieved on every cycle. A recorder connected to a thermocouple attached to the rectifier is used to verify not only the temperature range, but also the number of cycles.

#### D. Blocking Current Test Set

The blocking current test set is used to measure the leakage currents of the reverse blocking junction. The test set along with the functional block diagram of the circuit are shown in Figs. 31 and 32, respectively. The reverse blocking (leakage) currents are measured at the full rated a.c. voltage of 800 volts peak. These currents are measured at both room temperature ( $25^{\circ}\text{C}$ ) and at the maximum rated temperature ( $125^{\circ}\text{C}$ ) of the Device Under Test (DUT).




Figure 27 Forward On-State Voltage  
Test Set. The DUT was mounted  
at the top of the cooling air  
duct in the center of the  
photograph.




1/12/77 RER  
1/10/79 MFD

Figure 28 Forward "ON" Voltage Test Set - Portable

Block Diagram

Ref: MIL-STD-750B, Method 4226.1







Fig. 29 Thermal Fatigue Test Set  
 The DUT is mounted in  
 view in the center of the  
 chamber. The test  
 box of the

1/13/77  
1/10/79 MED

Figure 30 Thermal Fatigue Test Set  
Block Diagram

Ref S.S-477, para. 4.1.2






Fig. 34 Blocking Current Test Set.  
This set was used to study  
temperature as well as the  
composition with an or  
on a vacuum system (not  
shown) for the high tem-  
perature and reduced bar-  
ometric pressure tests.  
Reverse blocking currents  
are measured with this  
equipment.

Figure 32


Reverse Blocking Current Test Set - A. C. Method

1/7/77  
RER

Block Diagram

Ref: MIL-STD 750B, methods 1001.1, 4206.1 & 4211.1

(Grounded Enclosure)



The measurement is performed by monitoring the voltage drop across a calibrated resistor in series with the DUT. This enables an oscilloscope to be used to measure the peak current since the oscilloscope is a voltage rather than a current measuring device. Ohm's law converts the reading to the current.

#### E. Blocking Voltage Life Test

Rectifiers are life tested for 200 hours by subjecting them to reverse blocking voltages of 800 volts while at a temperature of 125°C. A 60 Hz 1/2 wave AC power supply is used for voltage power. The test set is shown in Fig. 33 and the functional block diagram is shown in Fig. 34.

Metering within the test set provides the temperature of the DUT, elapsed time, voltage and current. A jack is provided for the measurement of the peak voltage with an oscilloscope. Indicator lamps and high voltage fuses are included in the power supply to indicate whether a DUT has failed to block the high voltage during the tests. The test set is designed to test six devices simultaneously.

The power supply is connected through a voltage regulator to the primary power lines of the high temperature oven. In this way, the power and timing are removed from the DUT in the event of a power interruption that would reduce the oven temperature below the test value. An interlocked oven door also removes the high voltage from the DUT when the oven door is opened, thus, protecting the personnel.

This power supply is also used for the Reduced Barometric Pressure test for half wave voltage application to the DUT in the vacuum chamber.

#### F. Thermal Resistance Test Set

The thermal resistance test set is used to determine the thermal resistance between the junction and the base of the fins on the heat-pipe.

Prior to testing the rectifier, each device is calibrated by recording the forward voltage ( $V_F$ ) drop at 4.0 A as a function of temperature. At each selected temperature, sufficient time is taken to insure that the junction, the heat-pipes and the oven are all in thermal equilibrium. At 4.0 A,  $V_F$  versus temperature is interpreted from measurements of the  $V_F$  at temperatures between the selected temperatures.




Fig. 33 Blocking Voltage Life Test Set,  
including the temperature controlled  
oven. This oven is also used for  
the other high temperature tests.

1/7/77 RER  
1/10/79 MFD


Figure 34 Blocking Voltage Life Test/Barometric Pressure Test Set

Ref: SCS-477, para. 4.6.1


(Grounded Enclosure)

Block Diagram

Alternate I: Life Test



Alternate II: Barometric Pressure (reduced)





It is this characteristic of  $V_F$  versus temperature at 4.0 A which is employed to determine the junction temperature during the thermal resistance test. The difference between the junction temperature and the case temperature, which is measured with a thermocouple attached to the outside wall of the heat-pipe, divided by heating power is the thermal resistance.

When a rectifier is tested it is heated by passing rated current through the device. This heating current is interrupted every 50.0 ms for about 0.5 ms. During the interruption, the  $V_F$  is measured at the ..... calibration current of 4.0 A.

The test set is shown in Fig. 35. Fig. 36 is a functional block diagram of the circuit.

The thermal resistance of the Transcalent rectifier is a function of dissipation power and ambient temperature.

## VI. CONCLUSION AND RECOMMENDATIONS

The confirmatory sample phase of the program has been successfully completed on schedule as stipulated by the program evaluation chart (PERT). See Int. Tech. Rept. Jan. 1979.

No particular difficulties were involved in this phase of the program, and we are ready to proceed with the pilot run program when permission is obtained. It is suggested that this approval be given as early as possible so that this work can proceed on schedule.

We shall proceed with the preliminary pilot run report as quickly as possible since we recommended that a pilot run demonstration be given early in the pilot production run. This approach has the advantage of many parts and subassemblies being available to demonstrate sequential operations in a short amount of time.

All drawings and procedures will be updated to reflect the final design for the pilot run, namely, standard doped, webless wick and nonconvoluted cathode strain isolation rings. The reasons for the final design have already been discussed and verified in the body of this report.





Fig. 35 Thermal Resistance Test Set.  
The DUT is mounted in the end  
of the cooling air duct shown  
in the foreground.

THIS PAGE IS BEST QUALITY PRACTICABLE  
FROM COPY FURNISHED TO DDC

Figure 36 Thermal Resistance Test Set  
Block Diagram

1/10/79 MFD

Ref: MIL-STD-708, Method 1001



VII. DISTRIBUTION LIST

The following pages include the distribution list supplied by the Contracting Officer with the DD 1423 for the Interim Technical Report. That list will be utilized also for the distribution of the next Interim and the Final Technical Reports.

Dr. Paul E. Greene  
Dir. Solid State Lab.  
Hewlett Packard Co.  
1501 Page Mill Road  
Palo Alto, CA 94304

Mr. Gerald B. Herzog  
Staff Vice President  
Technology Centers  
RCA  
David Sarnoff Res. Ctr.  
Princeton, NJ 08540

Dr. George E. Smith  
Bell Telephone Labs, Inc.  
MOS Device Dept.  
600 Mountain Ave.  
Room 2A323  
Murray Hill, NJ 07974

Commander  
U.S. Army Electronics Command  
ATTN: DRSEL-TL-1  
Mr. Robert A. Gerhold  
Fort Monmouth, NJ 07703

Commander  
Harry Diamond Labs.  
2800 Powder Mill Rd.  
ATTN: DRXDO-RCC,  
Mr. Anthony J. Baba  
Adelphi, MD 20783

Commanding Officer  
Picatinny Arsenal  
ATTN: SARPA-ND-D-A-4  
Mr. Arthur H. Hendrickson  
Bldg. 95  
Dover, NJ 07801

Commanding General  
U.S. Army Missile Command  
ATTN: Mr. Victor Ruwe,  
DRSMI-RGP  
Redstone Arsenal, AL 35809

Commander  
U.S. Army Electronics Command  
ATTN: DRSEL-TL-BS  
Mr. George W. Taylor  
Fort Monmouth, NJ 07703

Commanding Officer  
U.S. Army Research Office  
P.O. Box 12211  
ATTN: Dr. Chas. Boghosian  
Research Triangle Park, NC 27709

Naval Research Laboratory  
ATTN: Dr. David F. Barbe,  
Code 5260  
4555 Overlook Avenue, SW  
Washington, DC 20375

Naval Electronics Lab Center  
ATTN: Mr. Charles E. Holland, Jr.  
Code 4300  
271 Catalina Blvd.  
San Diego, CA 92152

The Johns Hopkins Univ.  
Applied Physics Laboratory  
ATTN: Dr. Charles Feldman  
11100 Johns Hopkins Road  
Laurel, MD 20810

Commander  
Naval Surface Weapons Center  
ATTN: Mr. Albert D. Krall,  
Code WR-43  
White Oak  
Silver Spring, MD 20910

Commander  
RADC  
ATTN: Mr. Joseph B. Brauer, RBRM  
Griffiss AFB, NY 13441

NASA  
Geo. C. Marshall Space Flight Center  
ATTN: Dr. Alvis M. Holladay, Code EC-41  
Marshall Space Flight Center, AL 35812

NASA  
Langley Research Center  
Langley Station  
ATTN: Mr. Charles Husson, M/S 470  
Hampton, VA 23665

Dir. National Security Agency  
ATTN: Mr. John C. Davis, R55  
Fort George G. Meade, MD 20755

Commander  
U.S. Army Production  
Equipment Agency  
ATTN: AMXPE-MT  
(Mr. C. E. McBurney)  
Rock Island, IL 61201

Mr. Jack S. Kilby  
5924 Royal Lane  
Suite 150  
Dallas, TX 75230

Dr. Barry Dunbridge  
TRW Systems Group  
One Space Park  
Redondo Beach, CA 90278

Mr. Harold D. Toombs  
Texas Instruments, Inc.  
P.O. Box 5474; M/S 72  
Dallas, TX 75222

Commander, AFAL  
ATTN: AFAL/DEH  
Mr. Stanley E. Wagner  
Wright Patterson AFB,  
OH 45433

Lincoln Laboratory, MIT  
ATTN: Dr. Donald J. Eckl  
P.O. Box 73  
Lexington, MA 02173

RADC (ETSD)  
ATTN: Mr. Sven Roosild  
Hanscom AFB, MA 01731

General Electric Company  
Semi-Conductor Products Dept.  
Building 7, Box 42  
Syracuse, NY 13201

Micro-Electronics Laboratory  
Hughes Aircraft Company  
500 Superior Avenue  
Newport Beach, CA 92663

Silicon Transistor Corp.  
ATTN: Mr. P. Fitzgerald  
Katrina Road  
Chelmsford, MA 01824

Mr. Daniel Becker  
Reliability & Qual. Test Center  
Mannes Spacecraft Center  
Houston, TX 77058

Texas Instruments, Inc.  
Library M.S. 20  
P.O. Box 5012  
Dallas, TX 75222

Dr. S. Bakalar  
Transitron Electronic Corp.  
168 Albion Street  
Wakefield, MA 01880

Mr. R. Riel  
Westinghouse Electric Corp.  
R&D Center  
Pittsburgh, PA 15235

National Semi-Conductor Corp.  
ATTN: Mr. R. Bregar  
Danbury, CT 06810

Solitron Devices  
256 Oak Tree Road  
Tappan, NY 10983

Dr. L. Suelzle  
Delta Electronics Corp.  
2801 S. E. Main Street  
Irvine, CA 92714

Bell Laboratories  
ATTN: Mr. W. H. Hamilton  
Whippany, NJ 07981

Commander  
Naval Ships Res. & Dev. Center  
ATTN: W. Kohl (Bldg. 100-3)  
Annapolis, MD 21402

United Technologies Corp.  
Power Systems Division  
ATTN: Mr. Kenneth Lipman  
Box 109  
South Windsor, CT 06074

Martin Marietta  
ATTN: Mr. E. E. Buchanan  
P.O. Box 179  
Denver, CO 80201

J. J. Henry Co., Inc. Special Proj.  
Attn: Mr. Mike Saboe - NSRDC Study  
2341 Jefferson Davis Highway  
Arlington, VA 22202

Fermi National Accelerator Lab.  
ATTN: Mr. Frank S. Cilyo  
P.O. Box 500  
Batavia, IL 60510

Hughes Aircraft Company  
Ground Systems Group, . . .  
ATTN: Dr. Kal Sekhon  
Fullerton, CA 92634

Commander  
Navy Weapons Center  
ATTN: Mr. S. S. Lafon  
China Lake, CA 93555

Commander (2)  
U.S. Army Electronics Command  
ATTN: DRSEL-PP-I-PI  
Mr. William R. Peltz  
Fort Monmouth, NJ 07703

Commander (2)  
U.S. Army Mobility Equipment  
Research and Development Ctr.  
ATTN: STSFB-EAP  
Dr. Russ Eaton  
Fort Belvoir, VA 22060

Advisory Group on Electron Dev. (2)  
ATTN: Working Group on Pwr. Devices  
201 Varick Street  
New York, NY 10014

Mr. Ron Wade  
ATTN: ELEX-0151431  
Navla Electronic Sys. Command  
Washington, DC 20360

Dr. Robert Redicker  
Mass. Inst. of Technology (MIT)  
Building 13-3050  
Cambridge, MA 02139

Defense Electronics Supply Ctr.  
Directorate of Engineering  
and Standardization  
DESC-ECS (Mr. N. Hauck)  
1507 Wilmington Pike  
Dayton, OH 45401

General Instrument Corp.  
Semi-Conductor Prod. Group  
ATTN: Mr. G. Cohen  
600 W. John Street  
Hicksville, LI, NY 11802

Harry Diamond Laboratories  
ATTN: Technical Library  
Connecticut Avenue and  
Van Ness Street  
Washington, DC 20438

Jet Propulsion Laboratory  
ATTN: Mr. L. Wright  
Mail Stop 158-205  
4800 Oak Grove Drive  
Pasadena, CA 71103

NASA  
Lewis Research Center  
ATTN: Mr. Gail Sundberg (MS54-4)  
2100 Brook Park Road  
Cleveland, OH 44135

Commander  
AF Aero Propulsion Lab.  
ATTN: AFAL/PODI  
(Mr. Philip Herron)  
Wright Patterson AFB, OH 45433

Commander  
Naval Air Development Center  
ATTN: Mr. Howard Ireland (3043)  
Mr. Joseph Segrest  
Warminster, PA 18974

Commander  
NAVSEC Code 420 CTRBG  
ATTN: Mr. Arnold D. Hitt, Jr.  
801 Center Building  
Hyattsville, MD 20782

Delco Electronics  
ATTN: Dr. A. Barrett  
Mail Code 8106  
676 Hollister Avenue  
Goleta, CA 93017

NASA  
Johnson Space Center  
ATTN: Mr. E. Wood, Code EG2  
Houston, TX 77058

Garrett Air Research  
ATTN: Mr. Everett Geis  
2525 West 190 Street  
Torrance, CA 90509

Airesearch Manufacturing Co.  
ATTN: Mr. John Ashmore  
Electronic Systems  
2525 W. 190th Street  
Torrance, CA 90509

Garrett Air Research Mfg. Co. . . .  
of Arizona  
ATTN: Mr. R. N. McGinley  
P.O. Box 5217  
402 S. 36th Street  
Phoenix, AZ 85010

Naval Underwater Systems Center  
ATTN: Mr. George Anderson  
Code 3642  
Newport, RI 02840

Lockheed California Co.  
ATTN: Mr. W. W. Cloud  
Department 75-82  
Bldg. 63/3, Box 551  
Plant A-1  
Burbank, CA 91520

Dr. Roy Scott Hickman  
Chairman, Dept. of Mech & Environ.  
Engr.  
University of California  
Santa Barbara, CA 93106

Sanders Associates  
ATTN: Mr. A. Hurley  
NCAI - 6247  
95 Canal Street  
Nashua, NH 03061

Ohio Semitronics, Inc.  
1205 Chesapeake Ave.  
Columbus, Ohio 43212  
ATTN: Mr. A. E. Middleton

Defense Documentation Center (12)  
ATTN: DDC-IRS  
5010 Duke Street  
Cameron Station (Bldg. 5)  
Alexandria, VA 22314

NASA  
Scientific & Tech. Inf. Off./KSI  
Washington, DC 20541

Commander  
U.S. Army Electronics Command  
Communications Systems  
Procurement Branch  
Fort Monmouth, NJ 07703  
ATTN: Capt. H. John Patch/PCO  
DRSEL-PP-C-CS-1

TRW, Inc.  
Defense & Space Systems Group  
ATTN: Mr. Art Schoenfeld  
One Space Park  
Redondo Beach, CA 90278



# DISTRIBUTION WITHIN RCA-SSD

Dr. R. E. Simon  
055-191

G. J. Buchko/R. Beam  
003-953

T. T. Lewis  
058-632

H. F. Lebegern  
068-682

C. L. Rintz  
057-644

Library  
686.

E. D. Fleckenstein  
053-460

R. M. Bowes  
057-644

N. R. Hangen (2)  
073-637

P. Harvest  
087-963

S. W. Kessler  
086-963

J. V. Platt  
Somerville

D. R. Trout  
086-963

K. C. Harding  
Arlington

W. T. Burkins  
086-963

E. Schmitt  
Somerville

C. V. Reddig  
086-963

B. B. Adams  
086-963

A. J. Witkowski  
086-963

J. D. Schmitt  
057-634

R. M. Hopkins  
086-963

M. F. DeVito  
086-963

R. E. Reed (10)  
086-963

C. E. Doner  
086-963

J. Grosh/R. Bauder  
080-923

L. B. Denlinger  
086-963